

ELECTRICAL CABLE CHART

Part No.	Cable Assy Details	Cable No.	End Fittings	Qty.
YB3-82-90 (Issue 3D)	C-CC/4 (End A) ————— C★1 (End B) (8' 3")	C30	End A Plug A85 1	
	C-CC/4 (End A) ————— C-DT (End C) (12' 3")		Adapter, crimp pot J69 5	
			End B Lug 12 1	
			End C Lug 10 3	
	Cable detail:— B-R7-C-CC/4 ————— C★1-R7-★	C30	End detail BDS151 at end A; BDS149 at end B (Fit lug 12)	
YB3-82-197 (Issue 2G)	D R7-C-CC/4 ————— C-DT-R7 [1 E [2 F [★	C30	End detail BDS151 at end A; BDS149 at end B	
	R-CS/4 (End A) ————— R-C (End B) (9' 3")	C29	End A Socket E72 1	
			Outlet assy. P27 1	
			(For breakdown see page U43)	
			Sleeve P99 AR	
YB3-82-222 (Issue 4G)			End B Lug 12 2	
			(Supply loose in linen bag)	
	Cable detail:— B R8-R-CS/4 ————— R-C-R8 [K9 C [K8	C29	End detail BDS148 sht 5 at end A; BDS149 at end B	
	R-DA/G (End A) ————— R-AW/17 (End B) (8' 0")	C29 C101	End A Plug B7 1	
			Adapter, crimp pot J69 30	
			Sleeve, solder Q77 2	
			Sleeve R15 AR	
			Sleeve R14 AR	
			End B Plug A76 1	
			Adapter, crimp pot J69 30	
			Sleeve, solder Q77 2	
			Sleeve R15 AR	
			Sleeve R14 AR	
	Cable detail:— E R9-R-DA/C ————— R-AW/17-R9 [E Z [Z	C101	End detail BDS151 & BGA685	
	L screen of E at both ends F screen of Z at both ends	Screen	End detail BGA685	
	A B C D F G H J K M N P R S T U V W X			
	R9-R-DA/G ————— R-AW/17-R9	C29	End detail BDS151	

ELECTRICAL CABLE CHART

Part No.	Cable Assy Details	Cable No.	End Fittings	Qty.	
YB3-82-222 (continued)	a c d j p r s R9-R-DA/G — R-AW/17-R9 a c d j p r s				
YB3-82-255 (Issue 3E)	R-DA/H (End A) (3' 11") R-EK/X (End B) R-DA/H (End A) (3' 10") R-EK/Y (End C)	C29 C33	End A Plug Adapter, crimp pot Sleeve, solder Sleeve End B Socket Cover assy. End C Insert Cover assy. Sleeve, solder Sleeve	B49 J69 Q74 R17 E64 L58 E48 L56 Q74 R17	1 14 3 AR 1 1 1 1 3 AR
	Cable detail:— A L M B X C N R H screen of A, L, M, B, X, C, N, & R 2 Screen of 1, 3, 4, 5, 7, 9, 10, & 11 D U F J G E R9-R-DA/H — R-EK/Y-R9 8 12 1 2 3 4 R9-R-DA/H — R-EK/X-R9 1 2 3 4	C33	End detail BDS151 at end A		
		C29	End etail	BGA685	
		C29	End detail BDS151 at end A		
		C29	End detail BDS151 at end A		
YB3-82-738 (Issue 1E)	A-BC (End A) (2' 5") A-BB (End B) A-BC (End A) (1' 10") A-BD (End C)	C30	End A Plug Outlet assy. Sleeve End B Socket Outlet assy. Sleeve End C Socket Outlet assy. Sleeve	G29 P35 P99 E74 P34 P99 E74 P34 P99	1 1 AR 1 1 AR 1 1 AR
	Cable detail:— A B C D R2-A-BC — A-BB-R2 R2-A-BC — A-BD-R2 B A B A	C30 C30	End detail End detail	BDS148 BDS148	
YB3-82-802 (Issue 1H)	R10-C-BH/3 (End A) (5' 5") C/A15-R10 (End B)	C92	End A Plug End B Plug End detail	B45 B45 BDS160	1 1

ELECTRICAL CABLE CHART

Part No.	Cable Assy Details	Cable No.	End Fittings	Qty.
YB3-82-808 (Issue 1K) (S.O.O.)	S-AE/1-R10 (End A) (3' 3") R10-S-AQ (End B)	C92	End A Plug B45 1 Sleeve Q52 AR End B Plug H52 1 End detail BDS160	
YB3-82-809 (Issue 1G) (S.O.O.)	S-AE (End A) (3' 4") S-AP (End B)	C79	End A Plug A55 1 Adapter, crimp pot J69 3 End B Plug A86 1 Adapter, crimp pot J69 3	
	Cable detail:— A R10-S-AE S-AP-R10 E B	C79	End detail BDS151	
YB3-82-819 (Issue 1K) (S.O.O.)	R-AD/1-R10 (End A) (3' 3") R10-P-AQ (End B)	C92	End A Plug B45 1 Sleeve Q52 AR End B Plug H52 1 End detail BDS160	
YB3-82-820 (Issue 1H) (S.O.O.)	P-AD/2 (End A) (3' 3") P-AP (End B)	C79	End A Plug A55 1 Adapter, crimp pot J69 3 End B Plug A86 1 Adapter, crimp pot J69 3	
	Cable detail:— A R10-P/AD2 P-AP-R10 E B	C79	End detail BDS151	
YB3-82-843 (Issue 2B)	N-AJ (End A) (6' 8") N-B (End B)	C29	End A Lug 10 2 End B Lug 10 2	
	Cable detail:— 4 R6-N-AJ N-B-R6 5 E19 E30	C29	End detail BDS149	
YB3-82-909 (Issue B)	4-R9-C-DT (End A) (10' 3") C-Q-R9-F2 (End B)	C29	End A Lug 10 1 End B Lug 12 1 End detail BDS149	
YB3-82-971 (Issue 2B)	C-GJ (End A) (11' 1") C-GK (End B)	C29	End A Lug 10 3 End B Lug 10 3	

RESTRICTED

Buccaneer S. Mk. 2
Issued with A.L.43

ELECTRICAL CABLE CHART

Part No.	Cable Assy Details	Cable No.	End Fittings	Qty.
YB3-82-971 (continued)	Cable detail:— 8 R11-C-GJ — C-GK-R11 8 7 7 6 6	C29	End detail BDS149	
YB3-81-974 (Issue 2E)	C-GJ — C-DG (End A) (3' 6") (End B)	C29 C33	End A Lug Sleeve R17 10 Sleeve, solder Q83 1 End B Lug 12 3 Sleeve R17 AR	5 AR 1
	Cable detail:— 1 R11-C-GJ — C-DG-R11 R/5 2 R/2 3 R/8 4-R11-C-GJ — C-DG-R11-R/11 5 screen of 4	C29 C33 C29	End detail BDS149 End detail BDS149 & BGA685 End detail BDS149 & BGA685 at end A	
YB3-82-977 (Issue 2B)	★-R11-C★1 — C-GJ-R11-5 (End A) (6' 6") (End B)	C29	End A Lug 12 1 End B Lug 10 1	
YB3-82-978 (Issue 2A)	★-R11-C★1 — C-GK-R11-5 (End A) (7' 0") (End B)	C29	End A Lug 12 1 End B Lug 10 1 End detail BDS149	
YB3-82-982 (Issue 1E)	C★1 — C-FT (End A) (13' 6") (End B)	C29	End A Lug 12 1 Sleeve Q66 AR End B Lug 8 3	
	Cable detail:— ★-R2-C★1 — C-FT-R2-2 Link together C-FT-R2-2 C-FS-R2-2 C-FR-R2-2	C29 C29	End detail BDS149 End detail BDS149 at end B	
YB3-82-997 (Issue 1C)	C-GG — C-GK (End A) (2' 10") (End B) C-GG — C★1 (End A) (8' 9") (End C)	C29	End A Socket E72 1 Outlet assy. P27 1 Sleeve P99 AR End B Lug 10 2 End C Lug 12 1	
	Cable detail:— B R11-C-GG — C-GK-R11 7 A 8 C-R11-C-GG — C★1-R11-★	C29 C29	End detail BDS148 at end A & BDS149 at end B End detail BDS148 at end A & BDS149 at end B (Fit lug 12)	

RESTRICTED

ELECTRICAL CABLE CHART

Part No.	Cable Assy Details	Cable No.	End Fittings	Qty.
YB3-82-1000 (Issue 1F)	C-GK ————— C-DG (End A) (8' 4") (End B)	C29	End A	
		C33	Lug 10	5
			Sleeve, solder Q85	1
			Sleeve R17	AR
			End B	
YB3-82-1002 (Issue 1E)			Lug 12	4
			Sleeve R17	AR
	Cable detail:— 2 3 R11-C-GK — C-DG-R11 R/3 1 R/9 4-R11-C-GK — C-DG-R11-R/12 R/6 5 screen of 4	C29	End detail BDS149	
		C33	End detail BDS149 & BGA685	
		C29	End detail BDS149 & BGA685 at end A	
YB3-82-1002 (Issue 1E)	R-DZ ————— C-GJ (End A) (46' 9") (End B)	C29	End A	
			Plug H14	1
			Outlet assy. P27	1
			(For breakdown see page U43)	
			Sleeve P99	AR
YB3-82-1002 (Issue 1E)			End B	
			Lug 10	1
			(Supply in linen bag)	
	Cable detail:— C-R11-R-DZ ————— C-GJ-R11-2	C29	End detail BDS148 at end A & BDS149 at end B	